

PZM11 LL WR

PROFESSIONAL WEATHER-RESISTANT HEMISPHERICAL BOUNDARY
LAYER MICROPHONE



IT CAN STAND THE RAIN!

The PZM11 LL WR is a professional weather-resistant boundary layer microphone designed for fast-food restaurants, outdoor intercoms, toll booths, SOS telephones, theme-park security and the like. A plastic membrane inside the microphone protects the mic capsule from water damage. The PZM11 LL WR will work during and after rainfall. If water freezes on the membrane, the mic's frequency response will change but will return to normal when the ice melts and the membrane dries.

The PZM11 LL WR is powered by 12 – 24 V AC or DC, provides line-level output and can be plugged directly into a VCR line input without the need for a costly mic preamp.

HIGHLIGHTS

- » **Hemispherical polar pattern**
for clear, intelligible pickup of speech
- » **Weather-resistant model**
for outdoor use
- » **Line-level output**
connects directly to video recorders

APPLICATIONS

- » Outdoor intercoms
- » Toll booths
- » SOS telephones
- » Home automation

KEY SPECIFICATIONS

Transducer	Electret condenser
Polar pattern	Hemispherical
Audio Frequency Bandwidth	80 Hz to 10 kHz
Sensitivity	5 mV/Pa
Max. sound pressure level	100 dB
Equivalent noise level	26 dB (A)
Signal-to-noise level	68 dB (A)
Electrical impedance	75 ohms, balanced
Recommended Load Impedance	1000 ohms
Powering Interface	12 - 24 V AC or DC
Audio output	Line-level output, screw terminals
Finish	Silver. May be painted any color.
Depth	44 mm (1.7 in.)
Width	70 mm (2.8 in.)
Height	120 mm (4.5 in.)
Net Weight	71 g (2.5 oz.)
Box content	1x PZM11 LL WR 1x Wall plate
Item numbers	SKU: 3325H00010 EAN: 9002761024821 UPC: 885038 02482 8

