



## General Channel Specific

Channel 1

Button Mode

Momentary ▾

Button Function

Talk ▾

- Talk
- Talk with 18 kHz Tone
- All Talk
- Call
- IFB
- All IFB
- 18 kHz Tone
- 20 kHz Tone
- Disabled

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 2

Button Mode

Hybrid ▾

Button Function

Talk ▾

Program Dim

3 ▾

Headset Routing

and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 3

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

15 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 4

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

15 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 5

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

15 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 6

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

15 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 7

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

15 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor A ▾

Call Indication

Visual Only ▾

Channel 8

Button Mode

Hybrid ▾

Button Function

Talk ▾

IFB Program Dim

20 dB ▾

Headset Routing

Left and Ri ▾

Monitor Routing

Monitor B ▾

Call Indication

Visual And ▾