



Model 542X-Series Dante® Intercom Audio Engine Feature-by-Feature Comparison Chart

	Model 5421	Model 5422-01	Model 5422-02
Number of Channels	16	32	64
Number of Flows	16	32	32
Maximum Number of Groups	4	8	16
Party-Line (PL) Mode	•	•	•
Pass-Thru Mode		•	•
Summing Bus Mode		•	•
IFB Mode (VOX/TOX)		•	•
Audio Control Mode		In Development	In Development
Auto Mix	•	In Development	In Development
Custom Group Names		•	•
Configured using STcontroller	•		
Configured using Web Browser		•	•
Firmware Updating	USB	FTP	FTP
Ethernet Jacks	1	2	2
Redundant Ethernet		•	•
PoE Powering	•		
AC Mains Power		•	•
DC Power		•	•
Enclosure	1/2 Rack	1 RU	1RU
Availability Status (as of 21-Jul-20)	Active	Active	Active